

CFL Lamps										
Manufacturer	Model	Power	Compatibility	Number of bulbs *	Dimming curve **	Dimming mode **	Low Dimming Limit***	Maximum Dimming Limit***	Observations	
E27	HEITRONIC	19519	25W	Yes	1	Curve 2	Lead	25%	-	
	IKEA	SPARSAM	20W	Yes	1-13	Curve 2	Trail	35%	-	
		TORNADO	15W	Yes	1-2	Curve 2	Lead	2%	-	
	PHILIPS	PL-ELECTRONIC DIMMABLE	20W	Yes	1-4	Curve 2	Trail	2%	87%	
		SOFTONE	12W	Yes	1-2	Curve 2	Trail	6%	90%	
			12W	Yes	2	Curve 2	Trail	6%	96%	
	OSRAM	DULUX INTELLIGENT DIMMABLE	18W	Yes	1	Curve 2	Trail	20%	97%	
			18W	Yes	2-3	Curve 2	Trail	20%	-	
			11W	Yes	1-3	Curve 2	Lead	26%	70%	
	MEGAMAN	MM42102	11W	Yes	3	Curve 2	Lead	34%	82%	
			11W	Yes	1-2	Curve 2	Lead	12%	-	
		MM46012	11W	Yes	3	Curve 2	Lead	20%	-	
			18W	Yes	1-3	Curve 2	Trail	9%	75%	
18W			Yes	4-10	Curve 2	Trail	13%	88%		
GU10	HEITRONIC	19513	10W	Yes	1	Curve 2	Lead	12%	-	Flickering on the start of dimming.
	MEGAMAN	BR1411D	11W	Yes	1-2	Curve 2	Trail	5%	80%	

LED Lamps										
Manufacturer	Model	Power	Compatibility	Number of bulbs *	Dimming curve **	Dimming mode **	Low Dimming Limit***	Maximum Dimming Limit***	Observations	
E27	OSRAM	PARATHOM PRO PAR16 35 36° ADVANCED	5,2W	Yes	1-8	Curve 1 or Curve 2	Trail	-	-	
		PARATHOM CLASSIC A 60 ADVANCED	12W	Yes	1-10	Curve 2	Trail	-	97%	
		PARATHOM CL A 60	12W	Yes	1	Curve 1 or Curve 2	Trail	-	-	
	PHILIPS	MASTER LEDBULB MC DimTone	8W	Yes	1-9	Curve 1	Trail	-	75%	
		MASTER LEDbulb MV	17W	Yes	1-3	Curve 1 or Curve 2	Lead	-	-	
		LEDspot PAR 20	7W	Yes	1-2	Curve 1 or Curve 2	Lead	-	-	
		MASTER LEDbulb MV	12W	Yes	1	Curve 1 or Curve 2	Lead/Trail	-	-	
		MASTER LEDspot PAR 38 MV	18W	Yes	1-4	Curve 1	Trail	3%	-	
		MASTER LEDspot PAR 30s MV	12W	Yes	1-3	Curve 1 or Curve 2	Trail	-	-	
	MEGAMAN	LED GLOBE LG0708dv2	8W	Yes	1-3	Curve 2	Lead	4%	-	
		LED CLASSIC LG0408dv2	8W	Yes	1-3	Curve 2	Lead	5%	-	
		LG1907dv2	7W	Yes	1-9	Curve 1	Trail	-	70%	
	VERBATIM	Classic A	9W	Yes	1	Curve 1 or Curve 2	Trail	-	-	
		PAR38	18W	Yes	1-3	Lineal or Curve 2	Lead	12%	-	More than 3 bulbs cannot be dimmed.
	LEDA	?	Yes	1	Curve 1 or Curve 2	Lead	-	-		
	CALEX		7W	Yes	1	Curve 1 or Curve 2	Trail	-	98%	
	GU10	OSRAM	PARATHOM PRO PAR16 35 ADVANCED	8W	Yes	1-3	Curve 1 or Curve 2	Lead/Trail	-	-
PARATHOM PRO PAR16 35 ADVANCED			9W	Yes	1-3	Curve 2	Lead	4%	-	
BGENOSTORE RENOVABLES			9W	Yes	1-5	Curve 1	Trail	-	60%	
		ONLINE MR 16	5W	Yes	1-6	Curve 1 or Curve 2	Lead/Trail	-	-	
		LEDspot GU10 MV DIMMABLE	7W	Yes	1	Curve 2	Lead	3%	-	
PHILIPS		MASTER LEDspot MV	4W	Yes	1	Curve 2	Lead	5%	-	
		MASTER LEDspot MV	5,5W	Yes	1-4	Curve 2	Lead	25%	-	
BRICOLUX			3W	Yes	1-3	Curve 1	Trail	-	50%	
			6W	Yes	1	Curve 1 or Curve 2	Lead/Trail	-	-	
MEGAMAN		LR1108d-50H35D	8W	Yes	1	Curve 1 or Curve 2	Lead	-	-	
InteWatt		01-SLAGU10DNW	5W	Yes	2	Curve 1 or Curve 2	Lead/Trail	-	-	Only one bulb cannot be dimmed.
CONNECTOR LIBRE	FOKE	LED Stick (336 LEDs)	22W	Yes	1	Curve 2	Trail	-	-	

LED Lamps (12V)											
Manufacturer	Model	Transformer	Power	Compatibility	Number of bulbs *	Dimming curve **	Dimming mode **	Low Dimming Limit***	Maximum Dimming Limit***	Observations	
VERBATIM	MR16	Niko 320-00004	6W	Yes	1	Curve 2	Lead	-	98%		
		Niko 320-00003	6W	Yes	1	Curve 2	Lead	-	98%		
		Niko 320-00002	6W	Yes	1	Curve 1 or Curve 2	Lead	-	95%		
		MIMAVEN 150W	6W	Yes	1	Curve 1 or Curve 2	Lead	-	98%		
		MIMAVEN 100W	6W	Yes	1	Curve 1 or Curve 2	Lead	-	98%		
		KRS LTD. 105	6W	Yes	1	Curve 2	Lead	-	98%		
		Laytron TRI-50 ENC-C PTC	6W	Yes	1	Curve 2	Lead	-	95%		
		MCT 5402.0340.439	6W	Yes	1	Curve 2	Lead	-	95%		
		ELT TCE 5/23-E	6W	Yes	1	LED1 or LED2	Trail	-	73%		
		ELT TCE 7/23-E	6W	No							Flickering when dimming.
		OSRAM ET-ZE 60/220-240	6W	No							The load does not switch on.
		ThreeLine TT60	6W	No							Flickering when dimming.
		Niko 320-00101	6W	No							Flickering and overvoltage error when dimming.
		OSRAM HALOTRONIC HTL 225/230-240	6W	No							Overvoltage.
		OSRAM HALOTRONIC HTL 150/230-240	6W	No							Overvoltage.
		OSRAM HALOTRONIC HTL 70/230-240	6W	No							Overvoltage.
		OSRAM HALOTRONIC HTL 105 230-240	6W	Yes	1	Curve 1 or Curve 2	Trail	16%	68%		
		PHILIPS Primaline 105 230-240	6W	No							Overvoltage.
		PHILIPS Primaline 70 230-240	6W	No							Overvoltage.
		OSRAM	PARATHOM MR16 20 36 ^a ADVANCED	Niko 320-00004	5W	Yes	1-4	Curve 1 or Curve 2	Lead	-	97%
Niko 320-00003	5W			Yes	1-4	Curve 1 or Curve 2	Lead	-	-		
Niko 320-00002	5W			Yes	1-4	LED2	Lead	-	-		
MIMAVEN 150W	5W			Yes	1-4	Curve 1 or Curve 2	Lead	-	-		
MIMAVEN 100W	5W			Yes	1-4	Curve 1 or Curve 2	Lead	-	-		
KRS LTD. 105	5W			Yes	1-4	LED2	Lead	-	-	Maximum dimming limit for 1-2 units 90%.	
Laytron TRI-50 ENC-C PTC	5W			Yes	1-4	LED2	Lead	-	-	Maximum dimming limit for 1-2 units 90%.	
MCT 5402.0340.439	5W			No							Flickering and noise when dimming.
ELT TCE 5/23-E	5W			Yes	1-4	Curve 1 or Curve 2	Trail	-	-		
ELT TCE 7/23-E	5W			Yes	1-4	Curve 2	Trail	2%	-	Minimum and maximum dimming limit for 1 unit: 2% - 96%.	
OSRAM ET-ZE 60/220-240	5W			No							Low luminosity and open circuit error
ThreeLine TT60	5W			Yes	1-4	Curve 2	Trail	3%	87%	Flickering when there is only one lamp. Minimum and maximum dimming limit for 2 units 8% - 65%.	
Niko 320-00101	5W			Yes	1-4	Curve 2	Trail	2%	-		
OSRAM HALOTRONIC HTL 225/230-240	5W			Yes	1-4	Curve 2	Trail	-	59%		
OSRAM HALOTRONIC HTL 150/230-240	5W			No							Overvoltage.
OSRAM HALOTRONIC HTL 70/230-240	5W			Yes	1-4	Curve 2	Trail	-	-	Flickering when there is only one lamp. Minimum and maximum dimming limit for 2 units: 8% - 95%.	
OSRAM HALOTRONIC HTL 105 230-240	5W			Yes	1-4	Curve 2	Trail	5%	95%		
PHILIPS Primaline 105 230-240	5W			Yes	3-4	Curve 2	Trail	-	-	Flickering on the start of dimming.	
PHILIPS Primaline 70 230-240	5W			Yes	4	Curve 2	Trail	-	-	Flickering on the start of dimming.	
PARATHOM MR16 60 ADVANCED	Niko 320-00004			11W	Yes	1-3	Curve 2	Lead	30%	96%	Noise when dimming. Minimum and maximum dimming limit for 1 unit: 45% - 92%.
	Niko 320-00003		11W	Yes	1-3	Curve 2	Lead	30%	96%	Noise when dimming. Minimum and maximum dimming limit for 1 unit: 45% - 92%.	
	Niko 320-00002		11W	Yes	1-3	Lineal	Lead	15%	96%	Noise when dimming. Minimum and maximum dimming limit for 1 unit: 18% - 88%.	
	MIMAVEN 150W		11W	Yes	1-3	Lineal	Lead	33%	96%	Noise when dimming. Minimum and maximum dimming limit for 1 unit: 41% - 100%.	
	MIMAVEN 100W		11W	Yes	1-3	Lineal	Lead	24%	96%	Noise when dimming. Minimum and maximum dimming limit for 1 unit: 35% - 86%.	
	KRS LTD. 105		11W	Yes	1-3	Lineal	Lead	15%	85%	Noise when dimming. Minimum and maximum dimming limit for 1 unit: 19% - 72%.	
	Laytron TRI-50 ENC-C PTC		11W	Yes	1-3	Curve 2	Lead	33%	89%	Noise when dimming. Minimum and maximum dimming limit for 1 unit: 17% - 81%.	
	MCT 5402.0340.439		11W	Yes	1-3	Curve 2	Lead	23%	92%	Noise when dimming. Minimum and maximum dimming limit for 1 unit: 23% - 88%.	
	ELT TCE 5/23-E		11W	Yes	1-3	Curve 1 or Curve 2	Trail	-	-		
	ELT TCE 7/23-E		11W	Yes	1-3	Curve 1 or Curve 2	Trail	-	-	Blink on the start of dimming.	
	OSRAM ET-ZE 60/220-240		11W	Yes	1-3	Curve 1 or Curve 2	Trail	-	-	Blink on the start of dimming.	
	ThreeLine TT60		11W	No							Flickering on the start of dimming.
	Niko 320-00101		11W	Yes	1-3	Curve 1 or Curve 2	Trail	-	-	Flickering on the start of dimming.	
	OSRAM HALOTRONIC HTL 225/230-240		11W	Yes	2-3	Lineal	Trail	27%	98%		
	OSRAM HALOTRONIC HTL 150/230-240		11W	Yes	1-3	Curve 1 or Curve 2	Trail	-	-	Flickering on the start of dimming.	
	OSRAM HALOTRONIC HTL 70/230-240		11W	Yes	1-3	Curve 1 or Curve 2	Trail	-	-	Flickering on the start of dimming.	
	OSRAM HALOTRONIC HTL 105 230-240		11W	Yes	1-3	Curve 1 or Curve 2	Trail	-	-	Flickering on the start of dimming.	
	PHILIPS Primaline 105 230-240		11W	Yes	1-3	Curve 1 or Curve 2	Trail	-	-	Flickering on the start of dimming.	
	PHILIPS Primaline 70 230-240		11W	Yes	1-3	Curve 1 or Curve 2	Trail	-	-	Flickering on the start of dimming.	
	G5.3			Niko 320-00004	7W	Yes	1-2	Lineal	Lead	20%	98%
Niko 320-00003				7W	Yes	1-2	Curve 2	Lead	30%	-	Flickering on the start of dimming.
Niko 320-00002		7W		Yes	1-2	Lineal	Lead	20%	-	Flickering on the start of dimming.	
MIMAVEN 150W		7W		Yes	1-2	Lineal	Lead	25%	-	Flickering on the start of dimming.	
MIMAVEN 100W		7W		Yes	1-2	Lineal	Lead	20%	-	Flickering on the start of dimming.	
KRS LTD. 105		7W		Yes	1-2	Lineal	Lead	20%	90%	Flickering on the start of dimming.	
Laytron TRI-50 ENC-C PTC		7W		Yes	1-2	Lineal	Lead	22%	93%	Flickering on the start of dimming. Minimum and maximum dimming limit for 1 unit: 15%-83%.	
MCT 5402.0340.439		7W		Yes	1-2	Lineal	Lead	22%	92%	Flickering on the start of dimming.	

LED Lamps (12V)											
Manufacturer	Model	Transformer	Power	Compatibility	Number of bulbs *	Dimming curve **	Dimming mode **	Low Dimming Limit***	Maximum Dimming Limit***	Observations	
PHILIPS	MASTER LEDSPOT MR16 LV	ELT TCE 5/23-E	7W	Yes	1-2	Lineal	Trail	15%	97%	Flickering on the start of dimming.	
		ELT TCE 7/23-E	7W	Yes	1-2	Lineal	Trail	15%	97%	Flickering on the start of dimming.	
		OSRAM ET-ZE 60/220-240	7W	Yes	1-2	Lineal	Trail	18%	-	Flickering on the start of dimming. Minimum and maximum dimming limit for 1 unit: 15% - 57%.	
		ThreeLine TT60	7W	Yes	2	Lineal	Trail	18%	-	Flickering on the start of dimming.	
		Niko 320-00101	7W	Yes	1-2	Lineal	Trail	19%	-	Flickering on the start of dimming.	
		OSRAM HALOTRONIC HTL 225/230-240	7W	No						Overvoltage.	
		OSRAM HALOTRONIC HTL 150/230-240	7W	No						Overvoltage.	
		OSRAM HALOTRONIC HTL 70/230-240	7W	Yes	1-2	Lineal	Lead	30%	-	Flickering on the start of dimming.	
		OSRAM HALOTRONIC HTL 105 230-240	7W	Yes	1-2	Lineal	Lead	29%	-	Flickering on the start of dimming.	
		PHILIPS Primaline 105 230-240	7W	Yes	1-2	Curve 1	Trail	35%	80%	Flickering on the start of dimming. Minimum and maximum dimming limit for 1 unit:30% - 62%.	
		PHILIPS Primaline 70 230-240	7W	Yes	1-2	Curve 1	Trail	37%	82%	Flickering on the start of dimming. Minimum and maximum dimming limit for 1 unit:30% - 62%.	
		Niko 320-00004	10W	Yes	1	Lineal	Lead	15%	-	Flickering on the start of dimming.	
		Niko 320-00003	10W	Yes	1	Lineal	Lead	20%	-	Flickering on the start of dimming.	
		Niko 320-00002	10W	Yes	1	Lineal	Lead	20%	-	Flickering on the start of dimming.	
	MASTER LEDSPOT MR16 LV	MIMAVEN 150W	10W	Yes	1	Lineal	Lead	15%	-	Flickering on the start of dimming.	
		MIMAVEN 100W	10W	Yes	1	Lineal	Lead	15%	-	Flickering on the start of dimming.	
		KRS LTD. 105	10W	Yes	1	Curve 2	Lead	22%	96%	Flickering on the start of dimming.	
		Layrton TRI-50 ENC-C PTC	10W	Yes	1	Lineal	Lead	20%	90%	Flickering on the start of dimming.	
		MCT 5402.0340.439	10W	Yes	1	Curve 2	Lead	25%	96%	Flickering on the start of dimming.	
		ELT TCE 5/23-E	10W	Yes	1	Lineal	Trail	12%	-	Flickering on the start of dimming.	
		ELT TCE 7/23-E	10W	Yes	1	Lineal	Trail	12%	-	Flickering on the start of dimming.	
		OSRAM ET-ZE 60/220-240	10W	Yes	1	Lineal	Trail	25%	-	Flickering on the start of dimming.	
		ThreeLine TT60	10W	Yes	1	Lineal	Lead	20%	-	Flickering on the start of dimming.	
		Niko 320-00101	10W	Yes	1	Lineal	Lead/Trail	25%	-	Flickering on the start of dimming.	
		OSRAM HALOTRONIC HTL 225/230-240	10W	No						Overvoltage.	
		OSRAM HALOTRONIC HTL 150/230-240	10W	No						Overvoltage.	
		OSRAM HALOTRONIC HTL 70/230-240	10W	Yes	1	Lineal	Trail	25%	-	Flickering on the start of dimming.	
		OSRAM HALOTRONIC HTL 105 230-240	10W	Yes	1	Lineal	Trail	25%	-	Flickering on the start of dimming.	
	PHILIPS Primaline 105 230-240	10W	Yes	1	Lineal	Trail	15%	68%	Flickering on the start of dimming.		
	PHILIPS Primaline 70 230-240	10W	Yes	1	Curve 2	Trail	25%	65%	Flickering on the start of dimming.		
	VERBATIM	AR111	Niko 320-00004	16W	Yes	1	Curve 1 or Curve 2	Lead	-	-	
			Niko 320-00003	16W	Yes	1	Curve 1 or Curve 2	Lead	-	-	
			Niko 320-00002	16W	Yes	1	Curve 1 or Curve 2	Lead	-	-	
			MIMAVEN 150W	16W	Yes	1	Curve 1 or Curve 2	Lead	-	-	Noise in the transformer
MIMAVEN 100W			16W	Yes	1	Curve 1 or Curve 2	Lead	-	-	Noise in the transformer	
KRS LTD. 105			16W	Yes	1	Curve 1 or Curve 2	Lead	-	-		
Layrton TRI-50 ENC-C PTC			16W	Yes	1	Curve 1 or Curve 2	Lead	-	-		
MCT 5402.0340.439			16W	Yes	1	Curve 1 or Curve 2	Lead	-	-		
ELT TCE 5/23-E			16W	Yes	1	Curve 1 or Curve 2	Trail	-	93%		
ELT TCE 7/23-E			16W	Yes	1	Curve 1 or Curve 2	Trail	-	82%		
OSRAM ET-ZE 60/220-240			16W	Yes	1	Curve 1 or Curve 2	Trail	-	78%		
ThreeLine TT60			16W	No						Flickering when dimming.	
Niko 320-00101			16W	Yes	1	Curve 1 or Curve 2	Lead	-	-	Noise in the transformer	
OSRAM HALOTRONIC HTL 225/230-240			16W	Yes	1	Curve 1 or Curve 2	Trail	-	78%		
OSRAM HALOTRONIC HTL 150/230-240		16W	Yes	1	Curve 2	Lead	2%	-			
OSRAM HALOTRONIC HTL 70/230-240		16W	Yes	1	Curve 1 or Curve 2	Lead	-	-			
OSRAM HALOTRONIC HTL 105 230-240		16W	Yes	1	Curve 1 or Curve 2	Lead	-	-			
PHILIPS Primaline 105 230-240		16W	No						Flickering when dimming.		
PHILIPS Primaline 70 230-240		16W	Yes	1	Lineal	Lead	8%	-			
REFLED AR111		Niko 320-00004	10W	Yes	1-4	Curve 2	Lead	-	-		
		Niko 320-00003	10W	Yes	1-4	Curve 2	Lead	6%	-		
		Niko 320-00002	10W	Yes	1-4	Curve 2	Lead	13%	-		
		MIMAVEN 150W	10W	Yes	1-4	Curve 2	Lead	-	-		
		MIMAVEN 100W	10W	Yes	1-4	Curve 2	Lead	-	-		
		KRS LTD. 105	10W	Yes	1-4	Curve 2	Lead	4%	-		
		Layrton TRI-50 ENC-C PTC	10W	Yes	1-4	Curve 2	Lead	16%	-	Minimum dimming limit for 1 unit: 90%.	
		MCT 5402.0340.439	10W	Yes	1-4	Curve 2	Lead	12%	-		
		ELT TCE 5/23-E	10W	Yes	1-4	Curve 1 or Curve 2	Trail	-	-		
		ELT TCE 7/23-E	10W	Yes	1-4	Curve 2	Trail	2%	-		
		OSRAM ET-ZE 60/220-240	10W	Yes	1-2	Curve 2	Trail	-	-	Open circuit with more than 2 units	
		ThreeLine TT60	10W	Yes	2-4	Curve 2	Trail	15%	-	Minimum dimming limit for 2 units: 50%.	
		Niko 320-00101	10W	Yes	1-4	Curve 2	Trail	-	-		
		OSRAM HALOTRONIC HTL 225/230-240	10W	Yes	3-4	Lineal	Trail	17%	-		
OSRAM HALOTRONIC HTL 150/230-240		10W	No						Overvoltage.		
OSRAM HALOTRONIC HTL 70/230-240	10W	Yes	1-4	Curve 2	Trail	-	-				
OSRAM HALOTRONIC HTL 105 230-240	10W	Yes	1-4	Curve 2	Trail	-	-				
PHILIPS Primaline 105 230-240	10W	Yes	1-4	Curve 1 or Curve 2	Trail	-	-				
PHILIPS Primaline 70 230-240	10W	Yes	1-4	Curve 2	Trail	-	-				

LED Lamps (12V)											
Manufacturer	Model	Transformer	Power	Compatibility	Number of bulbs *	Dimming curve **	Dimming mode **	Low Dimming Limit***	Maximum Dimming Limit***	Observations	
G53	OSRAM	PARATHOM PRO LEDSPOT111 50 24° ADVANCED	Niko 320-00004	12W	Yes	1-3	Curve 1 or Curve 2	Lead	-	-	
			Niko 320-00003	12W	Yes	1-3	Curve 1 or Curve 2	Lead	-	-	
			Niko 320-00002	12W	Yes	1-3	Curve 2	Lead	-	-	
			MIMAVEN 150W	12W	Yes	1-3	Curve 1 or Curve 2	Lead	-	-	
			MIMAVEN 100W	12W	Yes	1-3	Curve 1 or Curve 2	Lead	-	-	
			KRS LTD. 105	12W	Yes	1-3	Curve 1 or Curve 2	Lead	-	98%	
			Layrton TRI-50 ENC-C PTC	12W	Yes	1-3	Curve 2	Lead	-	95%	
			MCT 5402.0340.439	12W	Yes	1-3	Curve 2	Lead	-	95%	
			ELT TCE 5/23-E	12W	Yes	1-3	Curve 1 or Curve 2	Trail	-	-	
			ELT TCE 7/23-E	12W	Yes	1-3	Curve 2	Trail	2%	75%	
			OSRAM ET-ZE 60/220-240	12W	Yes	1-2	Curve 1	Trail	-	-	
			ThreeLine TT60	12W	Yes	1-3	Curve 2	Trail	19%	95%	
			Niko 320-00101	12W	Yes	1-3	Curve 1 or Curve 2	Lead/Trail	-	-	
			OSRAM HALOTRONIC HTL 225/230-240	12W	Yes	1-3	Curve 2	Trail	3%	-	Minimum and maximum dimming limit for 1 unit:3% - 70%. Noise in the transformer with only 1 unit.
			OSRAM HALOTRONIC HTL 150/230-240	12W	Yes	1-3	Curve 1 or Curve 2	Trail	-	-	
			OSRAM HALOTRONIC HTL 70/230-240	12W	Yes	1-3	Curve 1 or Curve 2	Trail	-	-	
			OSRAM HALOTRONIC HTL 105 230-240	12W	Yes	1-3	Curve 2	Trail	-	-	
			PHILIPS Primaline 105 230-240	12W	Yes	2-3	Curve 1 or Curve 2	Lead/Trail	-	-	Flickering when dimming with only 1 unit
			PHILIPS Primaline 70 230-240	12W	Yes	1-3	Curve 1 or Curve 2	Trail	2%	-	
			PHILIPS	MASTER LEDSPOT AR111 LV	Niko 320-00004	15W	Yes	1-3	Lineal	Lead	26%
Niko 320-00003	15W	Yes			1-3	Lineal	Lead	35%	-	Flickering on the start of dimming. Minimum and maximum dimming limit for 1 unit:: 24%- 90%.	
Niko 320-00002	15W	Yes			1-3	Lineal	Lead	45%	95%	Flickering on the start of dimming.	
MIMAVEN 150W	15W	Yes			1-3	Lineal	Lead	20%	95%	Flickering on the start of dimming.	
MIMAVEN 100W	15W	Yes			1-3	Lineal	Lead	20%	95%	Flickering on the start of dimming.	
KRS LTD. 105	15W	Yes			1-3	Lineal	Lead	25%	85%	Flickering on the start of dimming. Minimum and maximum dimming limit for 1 unit:18% - 75%.	
Layrton TRI-50 ENC-C PTC	15W	Yes			1-3	Lineal	Lead	30%	85%	Flickering on the start of dimming. Minimum and maximum dimming limit for 1 unit:15% - 70%.	
MCT 5402.0340.439	15W	Yes			1-3	Lineal	Lead	20%	90%	Flickering on the start of dimming. Minimum and maximum dimming limit for 1 unit: 20% - 85%.	
ELT TCE 5/23-E	15W	Yes			1-3	Lineal	Trail	20%	80%	Flickering on the start of dimming. Minimum and maximum dimming limit for 1 unit:15% - 55%.	
ELT TCE 7/23-E	15W	Yes			1-3	Lineal	Trail	25%	65%	Flickering on the start of dimming. Minimum and maximum dimming limit for 1 unit: 20% -55%.	
OSRAM ET-ZE 60/220-240	15W	Yes			1-3	Curve 2	Trail	35%	80%	Flickering on the start of dimming. Minimum and maximum dimming limit for 1 unit:30% - 60%.	
ThreeLine TT60	15W	Yes			1-3	Lineal	Lead	30%	-	Flickering on the start of dimming.	
Niko 320-00101	15W	Yes			1-3	Lineal	Lead	35%	-	Flickering on the start of dimming.	
OSRAM HALOTRONIC HTL 225/230-240	15W	No								Overvoltage.	
OSRAM HALOTRONIC HTL 150/230-240	15W	No								Overvoltage.	
OSRAM HALOTRONIC HTL 70/230-240	15W	Yes			1-3	Lineal	Lead	25%	-	Flickering on the start of dimming.	
OSRAM HALOTRONIC HTL 105 230-240	15W	Yes			1-3	Lineal	Lead	25%	-	Flickering on the start of dimming.	
PHILIPS Primaline 105 230-240	15W	Yes			1-3	Curve 2	Trail	30%	70%	Flickering on the start of dimming. Minimum and maximum dimming limit for 1 unit:30% - 60%.	
PHILIPS Primaline 70 230-240	15W	Yes			1-3	Curve 1	Trail	45%	75%	Flickering on the start of dimming. Minimum and maximum dimming limit for 1 unit:30% - 60%.	

* This information is based in the test with DIMinBOX 1.0 and a specific number of bulbs of each type. It could control a higher number of bulbs but it is ALWAYS necessary to test that number of bulbs.

** The dimming curve and mode to configure in ETS parameters is based in the tests with the indicated number of bulbs. It is necessary to test the number of bulbs that will be installed with DIMinBOX 2CH.

*** Some bulbs flicker in low dimming levels or are only dimmable from a specific level, so it is necessary to set a Low Dimming Limit. And also, some bulbs flicker in high dimming levels, because of that, it is necessary to set a High Dimming Limit.